








































































TWIST-LOCK® DEVICES

RATING COLOR CODED BY VOLTAGE			15 AMPERE		20 AMPERE			30 AMPERE								
			RECEPTACLE / CONNECTOR BODY		PLUG / INLET		RECEPTACLE / CONNECTOR BODY		PLUG / INLET							
			Insulgrip®	Insulgrip®	Insulgrip®	Safety- Shroud®	Watertight Safety- Shroud®	Insulgrip®	Safety- Shroud®	Watertight Safety- Shroud®	Insulgrip®	Safety- Shroud®	Watertight Safety- Shroud®			
2 Pole / 2 Wire	125V	ML1	C: HBL7464V FR: HBL7468  ML-1R	P: HBL7465V FI: HBL7467  ML-1P												
	125V	L1	R: HBL7540 C: HBL7506C FR: HBL7526C  L1-15R	P: HBL7545C FI: HBL7524C  L1-15P												
	250V	L2			R: HBL7210B C: HBL7101C FR: HBL8809C		 L2-20R	P: HBL7102C FI: HBL8815C		 L2-20P						
2 Pole / 3 Wire Grounding	125V	ML2	C: HBL7593V C: HBL7593 AC: HBL7571 R: HBL7596N R: HBL7596 FR: HBL7598  ML-2R	P: HBL7594V P: HBL7594 AP: HBL7570 FI: HBL7595N FI: HBL7595 FI: HBL7591  ML-2P												
	125V	L5	R: HBL4700 R: HBL47CM00 C: HBL4729C C: HBL47CM29C AC: HBL4729CA FR: HBL4715C  L5-15R	P: HBL4720C P: HBL47CM20C AP: HBL4720CA FI: HBL4716C  L5-15P	R: HBL2310 R: HBL2323C R: HBL2310AR R: HBL2310SR R: HBL2310SR2 C: HBL2313 C: HBL23CM13 FR: HBL2316	R: HBL2310AR C: HBL2310SR R: HBL2310SR2 C: HBL2313	R: HBL2310SW C: HBL2313SW P: HBL2311 FI: HBL2315 AP: HBL23CM11	SP: HBL2311S FI: HBL2315	P: HBL2311SW FI: HBL2315SW  L5-20P	R: HBL2610 R: HBL2613 R: HBL2616 R: HBL26CM10 FR: HBL26CM13	R: HBL2610AR R: HBL2610SR R: HBL2610SR2 C: HBL2613	R: HBL2610SW C: HBL2613SW R: HBL2621S FI: HBL2625 P: HBL26CM11	P: HBL2611 FI: HBL2615 P: HBL26CM11	SP: HBL2611S FI: HBL2615	P: HBL2611SW FI: HBL2615SW P: HBL2621SW FI: HBL2625SW	
	250V	L6	R: HBL4550 C: HBL4579C FR: HBL4585C  L6-15R	P: HBL4570C P: HBL4570CA FI: HBL4586C  L6-15P	R: HBL2320 C: HBL2323 FR: HBL2326	R: HBL2320AR R: HBL2320SR R: HBL2320SR2 C: HBL2323	R: HBL2320SW C: HBL2323SW P: HBL2321 FI: HBL2325C	SP: HBL2321S FI: HBL2325	P: HBL2321SW FI: HBL2325SW  L6-20P	R: HBL2620 C: HBL2623 FI: HBL2626	R: HBL2620AR R: HBL2620SR C: HBL2623	R: HBL2620SW C: HBL2623SW	P: HBL2621 FI: HBL2625	SP: HBL2621S FI: HBL2625	P: HBL2621SW FI: HBL2625SW	
	277V AC	L7	R: HBL4750 R: HBL4779C FR: HBL4785C  L7-15R	P: HBL4770C AP: HBL4770CA FI: HBL4786C  L7-15P	R: HBL2330 C: HBL2333 FR: HBL2336	R: HBL2330AR R: HBL2330SR R: HBL2330SR2 C: HBL2333	R: HBL2330SW C: HBL2333SW P: HBL2331 FI: HBL2335	SP: HBL2331S FI: HBL2335	P: HBL2331SW FI: HBL2335SW  L7-20P	R: HBL2630 C: HBL2633 FI: HBL2636			P: HBL2631 FI: HBL2635		 L7-30P	
	480V AC	L8			R: HBL2340 C: HBL2343 FR: HBL2346		P: HBL2341 FI: HBL2345  L8-20R		 L8-20P	R: HBL2640 C: HBL2643 FI: HBL2646			P: HBL2641 FI: HBL2645		 L8-30P	
	600V AC	L9			R: HBL2350 C: HBL2353 FR: HBL2356		P: HBL2351 FI: HBL2355  L9-20R		 L9-20P	R: HBL2650 C: HBL2653 FI: HBL2656			P: HBL2651 FI: HBL2655		 L9-30P	
	125/250V AC	L10			R: HBL2360 C: HBL2363 FR: HBL2366		P: HBL2361 FI: HBL2365  L10-20R		 L10-20P	R: HBL2660 C: HBL2663			P: HBL2661 FI: HBL2665		 L10-30P	
	125/250V AC	ML3	C: HBL7484V FR: HBL7487N FR: HBL7487  ML-3R	P: HBL7485V FI: HBL7486N FI: HBL7486  ML-3P												
	125/250V AC	L14			R: HBL2410 C: HBL2413 FR: HBL2416	R: HBL2410AR R: HBL2410SR C: HBL2413	R: HBL2410SW C: HBL2413SW  L14-20R	P: HBL2411 FI: HBL2415	SP: HBL2411S FI: HBL2415	P: HBL2411SW FI: HBL2415SW  L14-20P	R: HBL2710 C: HBL2713 FI: HBL2716	R: HBL2710AR R: HBL2710SR C: HBL2713	R: HBL2710SW C: HBL2713SW	P: HBL2711 FI: HBL2715	SP: HBL2711S FI: HBL2715	P: HBL2711SW FI: HBL2715SW  L14-30P
	3Ø 250V AC	L15			R: HBL2420 C: HBL2423 FR: HBL2426	R: HBL2420AR R: HBL2420SR R: HBL2420SR2 C: HBL2423	R: HBL2420SW C: HBL2423SW  L15-20R	P: HBL2421 FI: HBL2425	SP: HBL2421S FI: HBL2425	P: HBL2421SW FI: HBL2425SW  L15-20P	R: HBL2720 C: HBL2723 FI: HBL2726	R: HBL2720AR R: HBL2720SR C: HBL2723	R: HBL2720SW C: HBL2723SW	P: HBL2721 FI: HBL2725	SP: HBL2721S FI: HBL2725	P: HBL2721SW FI: HBL2725SW  L15-30P
3Ø 480V AC	L16			R: HBL2430 C: HBL2433 FR: HBL2436	R: HBL2430AR R: HBL2430SR C: HBL2433SR2 C: HBL2433	R: HBL2430SW C: HBL2433SW  L16-20R	P: HBL2431 FI: HBL2435	SP: HBL2431S FI: HBL2435	P: HBL2431SW FI: HBL2435SW  L16-20P	R: HBL2730 C: HBL2733 FI: HBL2736	R: HBL2730AR R: HBL2730SR R: HBL2730SR2 C: HBL2733	R: HBL2730SW C: HBL2733SW	P: HBL2731 FI: HBL2735	SP: HBL2731S FI: HBL2735	P: HBL2731SW FI: HBL2735SW  L16-30P	
3Ø 600V AC	L17									R: HBL2740 R: HBL2743 FI: HBL2746	R: HBL2740AR R: HBL2740SR R: HBL2740SR2 C: HBL2743	R: HBL2740SW C: HBL2743SW  L17-30R	P: HBL2741 FI: HBL2745	SP: HBL2741S FI: HBL2745	P: HBL2741SW FI: HBL2745SW  L17-30P	
4 Pole / 4 Wire	3ØY 120/208V AC	L18			R: HBL2440 C: HBL2443 FR: HBL2446		 L18-20R	P: HBL2441 FI: HBL2445		 L18-20P	R: HBL2750 C: HBL2753 FI: HBL2756		 L18-30R	P: HBL2751 FI: HBL2755		 L18-30P
	3ØY 277/480V AC	L19			R: HBL2450 C: HBL2453 FR: HBL2456		 L19-20R	P: HBL2451 FI: HBL2455		 L19-20P	R: HBL2760 C: HBL2763 FI: HBL2766		 L19-30R	P: HBL2761 FI: HBL2765		 L19-30P
	3ØY 347/600V AC	L20			R: HBL2460 C: HBL2463 FR: HBL2466		 L20-20R	P: HBL2461 FI: HBL2465		 L20-20P	R: HBL2770 C: HBL2773 FI: HBL2776		 L20-30R	P: HBL2771 FI: HBL2775		 L20-30P
4 Pole / 5 Wire Grounding	3ØY 120/208V AC	L21			R: HBL2510 R: HBL2513 FR: HBL2516	R: HBL2510AR R: HBL2510SR C: HBL2513SR2 C: HBL2513	 L21-20R	P: HBL2511 FI: HBL2515	SP: HBL2511S FI: HBL2515	P: HBL2511SW FI: HBL2515SW  L21-20P	R: HBL2810 C: HBL2813 FI: HBL2816	R: HBL2810AR R: HBL2810SR R: HBL2810SR2 C: HBL2813	 L21-30R	P: HBL2811 FI: HBL2815	SP: HBL2811S FI: HBL2815	P: HBL2811SW FI: HBL2815SW  L21-30P
	3ØY 277/480V AC	L22			R: HBL2520 C: HBL2523 FR: HBL2526		 L22-20R	P: HBL2521 FI: HBL2525		 L22-20P	R: HBL2820 C: HBL2823 FI: HBL2826		 L22-30R	P: HBL2821 FI: HBL2825		 L22-30P
	3ØY 347/600V AC	L23			R: HBL2530 C: HBL2533 FR: HBL2536		 L23-20R	P: HBL2531 FI: HBL2535		 L23-20P	R: HBL2830 C: HBL2833 FI: HBL2836		 L23-30R	P: HBL2831 FI: HBL2835		 L23-30P
2P / 3W	347V AC	L24			R: HBL3720 C: HBL3723 FR: HBL3726		 L24-20R	P: HBL3721 FI: HBL3725		 L24-20P	R: HBL2600 C: HBL2603		 L25-30R	P: HBL2601 FI: HBL2605		 L25-30P
4P / 5W	3ØY 240/415V AC	L26									R: HBL2800 C: HBL2803	 L26-30R	P: HBL2801 FI: HBL2805		 L26-30P	

OTHER LOCKING DEVICES



Twist-Lock® DEVICES

The image displays six different types of Twist-Lock electrical connectors, arranged in two rows. The top row shows three connectors: a black and gold receptacle (R), a black and white connector body (C), and a white flanged inlet (FI). The bottom row shows three connectors: a black and white angled plug (AP), a white angled connector body (AC), and a white flanged receptacle (FR). A red arrow points to the flanged receptacle (FR) on the right.

R: RECEPTACLE
P: PLUG
AP: ANGLED PLUG

C: CONNECTOR BODY
AC: ANGLED CONNECTOR BODY
Δ: CORROSION RESISTANT

FI: FLANGED INLET
FR: FLANGED RECEPTACLE

SAFETY-SHROUD® TWIST-LOCK® DEVICES

The image displays four different models of safety shroud twist-lock devices. From left to right: AR is an angled receptacle with a blue shroud; SR is a straight receptacle with a blue shroud; SR2 is a straight raised receptacle with a blue shroud; and SP is a shrouded plug with a white shroud and a black plug. Each device is shown from a front-facing perspective.

AR **SR** **SR2** **SP**

R: RECEPTACLE
ANGLED = SUFFIX: AR
STRAIGHT = SUFFIX: SR
STRAIGHT RAISED = SR2

SP: SHROUDED PLUG
Mates with InSafeCOMP
CONNECTOR

HUBBELLCO® DEVICES

R: RECEPTACLE

P: PLUG
C: CONNECTOR BODY

F: FLANGED INLET
C: COVERED INLET

HUBBELL [®] DEVICES			
	RATING	RECEPTACLE	PLUG
2 Pole / 3 Wire Grounding	20A 125V AC "HOSPITAL USE ONLY"	R: HBL23000HG C: HBL23001HGB	P: HBL23014HGB
	20A 125V AC EX-DRY PROOF (CLASS 1, DIV. 1, GROUP C)	R: HBL24301 C: HBL24310	P: HBL24312
	20A 125V	R: HBL23030 C: HBL23032B	P: HBL23035B
	(Note: These devices are not interchangeable with any other Hubbelllock devices.)		
	20A 125V AC/DC	R: HBL23000G C: HBL23002GB	P: HBL23005GB
	(Note: These devices are not UL Listed and are for replacement use only in existing installations.)		
	50A 250V AC FOR MOBILE X-RAY	R: HBL25505 C: HBL25503	P: HBL25515 C: HBL25525
	60A 250V AC FOR MOBILE X-RAY	R: HBL25605 C: HBL25603	P: HBL25615 C: HBL25625
	30A 600V AC	R: HBL20403 C: HBL21414B	P: HBL21452B FF: HBL20418
	20A 250V AC		

3 Pole / 4 Wire Grounding	30A 600V AC 20A 250V DC WEATHER RESISTANT	R: HBL22CM427 C: HBL21420 Q: HBL21CM414B	P: HBL21CM415B FI: HBL22CM428 Q: HBL21447
	30A 480V AC	R: HBL20443 C: HBL20444B	P: HBL20445B
	60A 600V AC	R: HBL26410 C: HBL26420 C: HBL26421 C: HBL26418	P: HBL26419 FI: HBL26422
4P / 5W Gnd	30A 600V AC 20A 250V DC	R: HBL25403 R: HBL25250 C: HBL25414B	P: HBL25415B
	60A 600V AC	R: HBL26520 C: HBL26516 C: HBL26521	P: HBL26519 FI: HBL26522

Hubbell De Mexico, S.A. De C.V.
Ave. Coyoacan No. 1051
Col. Del Valle C.P. 03100 Mexico D. F.
(01 55) 91 51 99 99 (Phone)
(01 55) 91 51 99 88 (FAX)
www.hubbell.com.mx

WLCMNEMA17

HUBBELL PIN & SLEEVE CONFIGURATION CHART

IEC WATERTIGHT PIN & SLEEVE DEVICES AND CIRCUIT-LOCK® IEC FUSED & UNFUSED MECHANICAL INTERLOCKS

Rating / Configuration					Watertight Devices				Back Boxes		Cap		Circuit-Lock® IEC Mechanical Interlock			
Amps	Poles & Wires	Recept./Conn.	Plug/Inlet	Device Voltage	Receptacle	Plug	Connector	Inlet	Non-Metallic	Metallic	Closure Cap	Interlock Voltage	Unfused	Fused	Unfused	Mating Plug
16	2P 3W			100-130V	HBL316R4W	HBL316P4W	HBL316C4W		B82030N	B8201W B8301W	PC320					
				220-240V	HBL316R6W	HBL316P6W	HBL316C6W	HBL316B6W	B82030N	B8201W B8301W	PC320					
	3P 4W			380-415V AC	HBL416R6W	HBL416P6W	HBL416C6W		B82030N	B8201W B8301W	PC420					
				220/380V 240/415V	HBL516R6W	HBL516P6W	HBL516C6W	HBL516B6W	B82030N	B8201W B8301W	PC520					
20	2P 3W			125V AC	HBL320R4W	HBL320P4W	HBL320C4W	HBL320B4W	B82030N	B8201W B8301W	PC320					
				250V AC	HBL320R6W	HBL320P6W	HBL320C6W	HBL320B6W	B82030N	B8201W B8301W	PC320					
	3P 4W			480V AC	HBL320R7W	HBL320P7W	HBL320C7W	HBL320B7W	B82030N	B8201W B8301W	PC320					
				125/250V AC	HBL420R12W	HBL420P12W	HBL420C12W	HBL420B12W	B82030N	B8201W B8301W	PC420	120/240V AC				
	3P 4W			30 250V	HBL460R9W LP A460R9	HBL460P9W LP A460P9	HBL460C9W	HBL460B9W	B82030N	B8201W B8301W	PC420	30 240V	HBL420M12W			
				30 480V AC	HBL460R7W	HBL460P7W	HBL460C7W	HBL460B7W	B82030N	B8201W B8301W	PC420	30 480V AC	HBL420M17W			
	4P 5W			30 600V AC	HBL460R5W	HBL460P5W	HBL460C5W	HBL460B5W	B82030N	B8201W B8301W	PC420	30 600V AC	HBL420M15W			
				30Y 120/208V	HBL520R9W	HBL520P9W	HBL520C9W	HBL520B9W	B82030N	B8201W B8301W	PC520					
	4P 5W			30Y 277/480V	HBL520R7W	HBL520P7W	HBL520C7W	HBL520B7W	B82030N	B8201W B8301W	PC520					
				30Y 347/600V	HBL520R5W	HBL520P5W	HBL520C5W	HBL520B5W	B82030N	B8201W B8301W	PC520					
30	2P 3W			125V AC	HBL330R4W	HBL330P4W	HBL330C4W	HBL330B4W	B82030N	B8201W B8301W	PC3430	120V AC	HBL330M14W			
				250V AC	HBL330R6W	HBL330P6W	HBL330C6W	HBL330B6W	B82030N	B8201W B8301W	PC3430	240V AC	HBL330M16W			
	3P 4W			480V AC	HBL330R7W	HBL330P7W	HBL330C7W	HBL330B7W	B82030N	B8201W B8301W	PC3430	480V AC	HBL330M17W			
				125/250V AC	HBL430R12W LP L430R12	HBL430P12W LP L430P12	HBL430C12W	HBL430B12W	B82030N	B8201W B8301W	PC3430	125/250V AC	HBL430M12W	HBL430M1F12W		
	3P 4W			30 250V	HBL430R9W LP L430R9	HBL430P9W LP L430P9	HBL430C9W	HBL430B9W	B82030N	B8201W B8301W	PC3430	30 250V	HBL430M19W	HBL430M1F9W	HBL430M19WR	HBL430P9WR
				30 480V AC	HBL430R7W	HBL430P7W	HBL430C7W	HBL430B7W	B82030N	B8201W B8301W	PC3430	30 480V AC	HBL430M17W	HBL430M1F7W	HBL430M17WR	HBL430P7WR
	4P 5W			380-415V AC	HBL430R6W	HBL430P6W	HBL430C6W	HBL430B6W	B82030N	B8201W B8301W	PC3430					
				30 600V AC	HBL430R5W	HBL430P5W	HBL430C5W	HBL430B5W	B82030N	B8201W B8301W	PC3430	30 600V AC	HBL430M15W	HBL430M1F5W	HBL430M15WR	HBL430P5WR
	4P 5W			30Y 120/208V	HBL530R9W	HBL530P9W	HBL530C9W	HBL530B9W	B82030N	B8201W B8301W	PC530	30Y 120/208V	HBL530M19W			
				30Y 277/480V	HBL530R7W	HBL530P7W	HBL530C7W	HBL530B7W	B82030N	B8201W B8301W	PC530	30Y 277/480V	HBL530M17W	HBL530M1F7W		
	4P 5W			200/346V - 240/415V	HBL530R6W	HBL530P6W	HBL530C6W	HBL530B6W	B82030N	B8201W B8301W	PC530					
				30Y 347/600V	HBL530R5W	HBL530P5W	HBL530C5W	HBL530B5W	B82030N	B8201W B8301W	PC530	30Y 347/600V	HBL530M15W	HBL530M1F5W		
32	2P 3W			220-240V	HBL332R6W	HBL332P6W	HBL332C6W	HBL332B6W	B82030N	B8201W B8301W	PC3430					
				100-130V	HBL332R4W	HBL332P4W	HBL332C4W	HBL332B4W	B82030N	B8201W B8301W	PC3430					
	3P 4W			30 250V	HBL432R9W	HBL432P9W	HBL432C9W	HBL432B9W	B82030N	B8201W B8301W	PC3430					
				380V 50Hz 440V 60Hz	HBL432R3W	HBL432P3W	HBL432C3W	HBL432B3W	B82030N	B8201W B8301W	PC3430	380V 50Hz 440V 60Hz	HBL432M3W			
	4P 5W			220/380V 240/415V	HBL532R6W	HBL532P6W	HBL532C6W	HBL532B6W	B82030N	B8201W B8301W	PC530					
				30Y 120/208V	HBL532R9W	HBL532P9W	HBL532C9W	HBL532B9W	B82030N	B8201W B8301W	PC530					
	4P 5W								B82030N	B8201W B8301W	PC530					
									B82030N	B8201W B8301W	PC530					

Rating / Configuration				Watertight Devices				■ Back Boxes				Circuit-Lock® IEC Mechanical Interlock				
Amps	Poles & Wires	Recept./ Conn.	Plug/ Inlet	Device Voltage	Receptacle	Plug	Connector	Inlet	Non-Metallic	Metallic	Closure Cap	Interlock Voltage	Regular Service		Reverse Service	
													Unfused	Fused	Unfused	Mating Plug
60	2P 3W			125V AC					B860N	B8601W B8602W	PC60	120V AC				
				250V AC					B860N	B8601W B8602W	PC60	240V AC				
				480V AC					B860N	B8601W B8602W	PC60	480V AC				
	3P 4W			125/250V AC					B860N	B8601W B8602W	PC60	120/240V AC				
				30 250V					B860N	B8601W B8602W	PC60	30 240V				
				30 480V AC					B860N	B8601W B8602W	PC60	30 480V AC				
				380-415V AC					B860N	B8601W B8602W	PC60					
				30 600V AC					B860N	B8601W B8602W	PC60	30 600V AC				
	4P 5W			30Y 120/208V					B860N	B8601W B8602W	PC60	30Y 120/208V				
				30Y 277/480V					B860N	B8601W B8602W	PC60	30Y 277/480V				
				200/346V-240/415V					B860N	B8601W B8602W	PC60					
				30Y 347/600V					B860N	B8601W B8602W	PC60	30Y 347/600V				
63	2P 3W			220-240V					B860N	B8601W B8602W	PC60					
				30 250V					B860N	B8601W B8602W	PC60					
	3P 4W			380-415V AC					B860N	B8601W B8602W	PC60					
				30Y 120/208V					B860N	B8601W B8602W	PC60					
	4P 5W			200/346V-240/415V					B860N	B8601W B8602W	PC60					
				220/380V-240/415V					B860N	B8601W B8602W	PC60					
100	2P 3W			125V AC					B8100N	B81001W B81002W	PC100					
				250V AC					B8100N	B81001W B81002W	PC100	240V AC				
				480V AC					B8100N	B81001W B81002W	PC100					
	3P 4W			125/250V AC					B8100N	B81001W B81002W	PC100	120/240V AC				
				30 250V					B8100N	B81001W B81002W	PC100	30 240V				
				30 480V AC					B8100N	B81001W B81002W	PC100	30 480V AC				
				30 600V AC					B8100N	B81001W B81002W	PC100	30 600V AC				
				30Y 120/208V					B8100N	B81001W B81002W	PC100	30Y 120/208V				
	4P 5W			30Y 277/480V					B8100N	B81001W B81002W	PC100					
				30Y 347/600V					B8100N	B81001W B81002W	PC100					
	125	2P 3W			220-240V					B8100N	B81001W B81002W	PC100				
				380-415V AC					B8100N	B81001W B81002W	PC100					
4P 5W				220/380V-240/415V					B8100N	B81001W B81002W	PC100					